

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18
- C6V2						1	1			5,8	6,2	6,6	40	+4,0		układy stabilizacji i ograniczenia napięcia	
- C6V8						1	1,5			6,4	6,8	7,2	15	+4,0			
- C7V5						1	1,5			7,0	7,5	7,9	10	+5,0			
- C8V2						1	2			7,7	8,2	8,7	10	+5,5			
- C9V1						1	3			8,5	9,1	9,6	15	+6,0			
- C10						1	6			9,4	10	10,6	15	+6,5			
- C11						1	7			10,4	11	11,6	20	+7,0			
- C12						1	8			11,4	12	12,7	20	+7,0			
- C13						1	9			12,4	13	14,1	25	+7,5			
- C15						1	10			13,8	15	15,6	30	+7,5			
- C16						1	11			15,3	16	17,1	40	+8,0			
- C18						1	12			16,8	18	19,1	55	+8,0			
- C20						1	14			18,8	20	21,2	55	+8,0			
- C22						1	15			20,8	22	23,3	58	+8,5			
- C24						1	16			22,8	24	25,6	80	+8,5			
- C27						1	1			25,1	27	28,9	80	+8,5			
- C30						1	1			28	30	32	90	+9,0			
- C33						1	1			31	33	35	90	+9,0			
- D3V3						30	1			2,9	3,3	3,7	100	-6,0			
- D3V9						10	1			3,5	3,9	4,3	100	-5,5			
- D4V7						2	1			4,1	4,7	5,2	90	-2,5			
- D5V6						1	1			5,0	5,6	6,3	60	+3,0			
- D6V8						1	1,5			6,0	6,8	7,5	15	+4,5			
- D8V2						1	2			7,3	8,2	9,2	10	+5,5			
- D10						1	6			8,8	10	11	15	+6,5			
- D12						1	8			10,7	12	13,4	20	+7,0			
- D15						1	10			13	15	16,5	30	+7,5			
- D18						1	12			16	18	20	55	+8,0			
- D22						1	15			19,6	22	24,4	58	+8,5			
- D27						1	18			24,1	27	30	80	+8,5			
- D30						1	20			27	30	33	90	+9,0			
- D33						1	22			29,7	33	36,3	90	+9,0			
E2P 687- - OV75	0,02	0,1	150	-25 ... +85	-55 ... +150	1	6			0,7	0,8	0,85 ^{2/}				1/	08 22