

FUNCTION GENERATOR METEX MXG-9802 / MXG-9810

Features

- 8 digit FND Display for Frequency
- Frequency output: 0.2Hz – 2MHz (MXG-9802), 1Hz – 10MHz (MXG-9810)
- Sine, Square, Triangle, Ramp, Pulse, TTL level, Skewed
- Variable Symmetry, Amplitude
- Built in Frequency counter: Channel A – 1Hz – 20MHz, Channel B – 20MHz – 2.7GHz



Specification

Frequency Range	0.2Hz –2MHz (MXG-9802)	
	1Hz – 10MHz (MXG-9810)	
VCF Voltage Level	0 – 10VDC	
Output Impedance	50Ω fixed	
Output Amplitude	2V _{pp} – 20V _{pp} Open Load	
	1V _{pp} – 10V _{pp} 50Ω at Load	
Attenuator	-20dB	
Frequency Variable	20:1 or more	
Offset Variable Range	Max: ±10VDC	
Symmetry Variable Range	3:1 or more	
Information	Dimensions	213 mm x 260 mm x 80 mm
	Power Requirements	220/240VAC, 50/60Hz
	Accessories	Manual, Power cord, BNC-BNC cable



GLOBAL FOCUS Ltd.

1119 Budapest, Etele str. 59-61.
Hungary

Tel: +36 1 481-1233, +36 1 481-1231, +36 1 481-1161, +36 1 481-1162

Fax: +36 1 203-4355

E-mail: gmark@mta.mmsz.hu